


## 1. Names and Parts




- |  |                      |
|--|----------------------|
| 1. Camera Lens                             | 8. Record (Red) LED  |
| 2. Microphone                              | 9. Power (Blue) LED  |
| 3. USB port                                | 10. Default Button   |
| 4. Wi-Fi Switch                            | 11. Reset Key        |
| 5. Continuous Rec/<br>Motion Detection Rec | 12. Memory Card Slot |
| 6. IP (Green) LED                          | 13. DC 5V In         |
| 7. Wi-Fi (Orange) LED                      | 14. Power Button     |

※ No microphones are available for USA market


1

## 2. Package Content



## 3. Recording Operation

- 3.1 Insert memory card into slot (12).
- 3.2 Plug the 5V wall adapter power supply into an electrical outlet.



※ Please note that device cannot be powered on if no memory card is inserted into the device.

2

3.3 Slide (14) to Front and blue LED (9) will be solid on. The system initialization takes around 40 seconds. With the presence of the red LED (8), it indicates that the recording is ongoing.

### 3.4 Connecting Your Phone to DVR

Slide (4) to "On" and the blinking orange LED (7) suggests that the unit is ready for P2P connection. For more details about the P2P connection guide, please refer to the IP Quick Guide.

### 3.5 Reset Wi-Fi Password and SSID

In case of Wi-Fi password lost or forgotten, press and hold the default button (10) for at least 4 seconds and shorter than 10 seconds; You will see all LED indicators turning on and then red, green and orange LED turning off. After 40 seconds, the presence of the flashing orange LED (7) indicates that the unit is ready to start the P2P connection again (P2P password: 88888888).

### 3.6 Restore to Factory Setting

To restore all settings back to factory default, press and hold the default button (10) for longer than 10 seconds; You will see all LED indicators turning on and then red, green and orange LED turning off. After 40 seconds, all the settings will be restored to factory default settings. Orange LED (7) will flash, indicates that the unit is restored to factory setting.

※ Please note that press and hold default button less than 4 seconds will be invalid.

※ Please note each time the device is switched to P2P or IP connection, the system initialization takes around 40 seconds.

※ During reset or restore process, Wi-Fi switch must be turned on to observe the orange LED.

3

## 4. LED indicators

LED Indicators	Device Status
Solid Blue LED	Power On
Solid Red LED	Recording On
Blinking Orange LED	Seaching P2P
Solid Orange LED	P2P Connected
Blinking Green LED	Seaching IP
Solid Green LED	IP Connected

## 5. Continuous / Motion Detection Recording

5.1 For continuous recording, slide (5) to C.

5.2 For Motion Detection recording, switch (5) to M.

After 10 seconds of system initialization, the unit will be ready for Motion Detection recording. Once the unit detects a movement, it will start recording and the red LED (8) will be on.

5.3 For snapshot function, please refer to the IP Quick Guide.

5.4 You can also use the PV Cam Viewer to change the recording mode. For further details, please refer to IP Quick Guide.

## 6. Retrieving Video Footage

6.1 With memory card in the DVR, connect micro USB end (3) to and the other end to the computer. The blue LED will be on and computer detects the storage. Users may browse and operate the storage as typical folder directory.

4

6.2 Remove memory card from DVR. Insert memory card into a card reader or memory card slot of computer. The storage will be detected and user may browse and operate it as folder directory, for example, rename, copy and paste, delete, duplicate.

※ Please note that video files will be named as V+year+month+day+time; e.g. V20191130112001

## 7. Date and Time Setting (for Windows system)


- 7.1 From the desktop right-click to open Notepad, create a text file named settime.txt
- 7.2 On the first line of the file, enter date and time information as year.month.day hours.minutes.seconds. For example, suppose the time is December 16, 2019 21:00. Then enter 2019.12.16 21:00:00
- 7.3 Save the file to the root directory of the memory card.
- 7.4 Insert the memory card into the slot, and power on the device. The date and time setting is now completed. Note that when date and time setting is completed, the settime.txt file should not be visible when you connect the device to the computer again.

※ Do not remove serial number stickers! Warranty is invalid if the sticker is tampered!

※ This product is for Law Enforcement and Home Security Use Only!

5

## 8. Open The Cover



Hold the side of the DVR and take the cover in red arrow direction. The cover will then be opened.


6

## 9. Specification

Built-in Camera Module	
Built-in Image Sensor	1/2.9" progressive CMOS sensor
Sensor Resolution	2000x1121
Sensor Sensitivity	0.1 Lux @ F 2.0
Lens F/No.	F 2.0
Focal Length	4.3mm
Angle of View	78.2°
Video Spec.	
Algorithm	H.264, JPEG
File Format	MOV, JPG
Video Recording Mode	Auto/Manual/Motion Detection
Recording Capability	1920x1080, 1280x720, 848x480
Frame Rate	Up to 30 fps
Photo Capability	2M(1600*1200)
Wi-Fi	
Wi-Fi	Built-in Wi-Fi Module(IEEE 802.11b/g/n)
Wi-Fi Protocol	TCP/IP
Storage & I/O	
Memory Type	Memory Card ( Support up to 64GB)
Data Interface	Mini USB 2.0
Misc.	
Date/Time Table	YYYY/MM/DD, HH:MM:SS
Snapshot	recording and playback video (via smartphone)
Power	
Power Input	DC5V 2A
Recording time	500 min @ 1920x1080 resolution ( 16GB memory card )

7

## PV-AP10i Air Purifier Design DVR Quick Guide



LawMate, innovation never stops

**LawMate**<sup>®</sup>