


PRODUCT TECHNICAL DATASHEET EDGE1/BOX



CODE	DESCRIPTION		PCS/PALLET
EDGE1/BOX	Digital control 36V for 2 BRUSHLESS motor, with plastic box.		50
PRODUCT TECHNIC	CAL SPECIFICATIONS		
Power line supply		230V AC - 50 Hz	
Operating temperatur	e	-10+55 C°	
Protection level		IP54	
N. motors activated		2 Brushless Motor	
Max power per motor		250W	
Max courtesy light cha	arge	100W 230V AC - 40W 24V AC/DC	
Max power gate open	light	3W (24V DC)	
Max voltage accessor	ries output	20W (24V DC)	
Eletrical-Lock max po	wer	15W (12V DC)	
Flash light voltage		24V DC	



25W

Optional



Max flashing light charge

Battery

PRODUCT ACCESSORIES



B71/BCHP/EXT

Kit for emergency batteries charger
for Brushless digital controller
EDGE1/BOX - B70/1DCH 36V DC
with plug-in card, with 2 recovery
batteries 12V DC, 4.5 Ah. Box case
included.



B71/BCHP/BOX
Kit for emergency batteries charger
for Brushless digital controller
EDGE1/BOX - B70/1DCHP 36V DC.
Box case included and without
recovery batteries.



B71/PBX36/BOX
Hybrid inverter, "Network Assisted"
version, for powering the
automation. Also provides a batterycharger function thanks to the
connection to the solar panels or
mains supply for powering the 36V
DC brushless digital controllers with a
mains voltage of 230V AC.



B71/PBX36/B0X/115
Hybrid inverter, "Network Assisted"
version, for powering the
automation. Also provides a batterycharger function thanks to the
connection to the solar panels or
mains supply for powering the 36y
DC brushless digital controllers with a
mains voltage of 115V AC.



B71/PBX/BOX Hybrid inverter, "Full Solar" version, for powering the automation. Also provides a battery-charger function thanks to the connection to the solar panels for powering the brushless digital controllers.



B74/BCONNECT
Module WI-FI B-CONNECT - Remote management and programming system in IP and CLOUD web browser mode via WI-FI hot spot P2P connection for Brushless control units (B70/2ML - EDGE1 - CTRL - CTRL/P - B70/1DCHP).

