



FireProtect

Wireless smoke and heat detector with sounder

Wireless fire detector quickly detects smoke and sharp jumps in temperature to raise an alert in case of danger. A built-in siren generates 85 dB at a distance of 1 m to warn those who are nearby.

Maximum Performance

- Communicates at a distance of up to 1,300 m from the hub
- Delivers an alarm signal within 0.15 s
- Interconnected alarms feature to simultaneously activate sirens in all the fire detectors within the system
- Operates up to 4 years on the pre-installed batteries

Effortless Operation

- Always on, always ready to detect fire and smoke
- False-alarm prevention algorithms
- Features options for manual and automatic smoke chamber checks
- Two-way communication with the hub for testing and configuring
- Can operate independently from hub, notifying of danger with a built-in siren

Simple Installation



Use the QR code to connect the device to the hub



Use the SmartBracket to mount the device without disassembling it



Open the app to test connection quality and configure device settings

Bulletproof Protection



Tampering alarm



Data encryption



Device forgery prevention

FireProtect Plus



- Features an additional CO sensor
- Alerts about the dangerous level of carbon monoxide to prevent poisoning

Tech Specs

- Color: white/black
- Installation: indoors
- Radio communication range: up to 1,300 m
- Compatibility: all hubs & ReX
- Sensing element: photoelectric and temperature sensors
- Activation threshold: $+59^{\circ}\text{C} \pm 2^{\circ}\text{C}$, or if the temperature rises by 30° in under 30 minutes
- Type of indication: sound/light
- Built-in siren volume: 85 dB
- Main power supply: two CR2 batteries, pre-installed
- Backup battery: CR2032, pre-installed
- Battery life: up to 4 years
- Operating temperature range: from 0°C to $+65^{\circ}\text{C}$
- Permissible humidity: up to 80%
- Dimensions: $132 \times 132 \times 31$ mm
- Weight: 220 g

