

VERSA-MCU

WIRELESS SYSTEM CONTROLLER

The **VERSA-MCU** module enables expansion of the **VERSA** control panels with wireless 433 MHz detectors. Up to 30 detectors may be added to a **VERSA** panel using this module. Owing to its compact casing, the **VERSA-MCU** module may be easily installed in an optimum location.

- supports up to 30 **MICRA** system detectors
- supports 433 MHz pilots
- support for **MRU-300** radio signal repeater
- dedicated for **VERSA** central control panels
- programming the controller settings via a service menu of a **DLOADX** central control panel and its software
- device disassembly not required for software update
- can be installed in any convenient place thanks to its small casing



TECHNICAL DATA

Number of supported remote control keyfobs	30
Supply voltage	12 V DC
Enclosure dimensions	24 x 110 x 27 mm
Operating temperature range	-10 °C...+55 °C
Standby mode current consumption	24 mA
Max. current consumption	29 mA
Weight	30 g
Maximum humidity	93±3%
Environmental class according to EN50130-5	II
Number of supported wireless detectors	30
Supported keyfobs	MPT-300, P-2, P-4, T-1, T-2, T-4
Supported wireless detectors	MFD-300, MMD-300, MPD-300, MSD-300
Keyfob and wireless detector operating frequency band	433,05 ÷ 434,79 MHz

