

PRODUCT TECHNICAL DATASHEET

EDGE1/BOX



CODE	DESCRIPTION	PCS/PALLET
EDGE1/BOX	Digital control 36V for 2 BRUSHLESS motor, with plastic box.	50

PRODUCT TECHNICAL SPECIFICATIONS

Power line supply	230V AC - 50 Hz
Operating temperature	-10+55 C°
Protection level	IP54
N. motors activated	2 Brushless Motor
Max power per motor	250W
Max courtesy light charge	100W 230V AC - 40W 24V AC/DC
Max power gate open light	3W (24V DC)
Max voltage accessories output	20W (24V DC)
Electrical-Lock max power	15W (12V DC)
Flash light voltage	24V DC
Max flashing light charge	25W
Battery	Optional
Maximum dimension product in mm (L x W x H)	330 x 230 x 115
Product weight packed (Kg)	5,8
Number items per pallet	50

PRODUCT ACCESSORIES



B71/BCHP/EXT
Kit for emergency batteries charger for Brushless digital controller EDGE1/BOX - B70/1DCHP 36V DC with plug-in card, with 2 recovery batteries 12V DC, 4.5 Ah. Box case included.



B71/BCHP/BOX
Kit for emergency batteries charger for Brushless digital controller EDGE1/BOX - B70/1DCHP 36V DC. Box case included and without recovery batteries.



B71/PBX36/BOX
Hybrid inverter, "Network Assisted" version, for powering the automation. Also provides a battery-charger function thanks to the connection to the solar panels or mains supply for powering the 36V DC brushless digital controllers with a mains voltage of 230V AC.



B71/PBX36/BOX/115
Hybrid inverter, "Network Assisted" version, for powering the automation. Also provides a battery-charger function thanks to the connection to the solar panels or mains supply for powering the 36V DC brushless digital controllers with a mains voltage of 115V AC.



B71/PBX/BOX
Hybrid inverter, "Full Solar" version, for powering the automation. Also provides a battery-charger function thanks to the connection to the solar panels for powering the brushless digital controllers.



B74/BCONNECT
Module WI-FI B-CONNECT - Remote management and programming system in IP and CLOUD web browser mode via WI-FI hot spot P2P connection for Brushless control units (B70/2ML - EDGE1 - CTRL - CTRL/P - B70/1DCHP).