

### TrackMix-WiFi-IP-Camera-Specifications

	Model	Reolink TrackMix WiFi
<b>Video &amp; Audio</b>	Image Sensor	1/3"+1/2.8"CMOS Sensor
	Video Resolution	Up to: 3840 x 2160 (8.0 megapixels) at 25 frames/sec
	Lens	f=2.8mm@F=1.6, f=8mm@F=1.6
	Video Format	H.264,H.265
	Field of View	Horizontal: 104 °38 ° Vertical: 60 °21 °
	Zoom Mode	6X hybrid zoom
	Day & Night	IR-cut filter with auto-switching
	Infrared Night Vision	Up to 15 meters (50ft) (LED: 2pcs/850nm)
	Color Night Vision	Spotlights: 2pcs/6500K/450 lumens
<b>Power</b>	Audio	Two-way audio
	DC Power	DC 12.0V=2A, <12W
<b>Interface</b>	Power	DC power port
	System	Reset button
	Ethernet	One 10M/100Mbps RJ45
	Storage	Micro SD card slot (Max. 256GB)
	Audio	Built-in microphone and speaker
<b>Pan&amp;Tilt</b>	Pan &Tilt Range	Pan: 355 °, Tilt: 0 °~90 °
	Pan Speed	2.5 °90 °/s (Speed can be set)
	Tilt Speed	1.5 °60 °/s (Speed can be set)
	Preset	32
	Auto Tracking	Support
<b>Wi-Fi</b>	Wireless Standard	IEEE 802.11a/b/g/n
	Operating Frequency	2.4GHz/5GHz
	Wireless Security	WPA-PSK/WPA2-PSK
<b>Software Features</b>	Frame Rate	Mainstream: 2fps - 25fps Substream: 4fps - 20fps
	Code Rate	Mainstream: 4096Kbps -8192Kbps Substream: 128Kbps -1228Kbps
	Browsers Supported	Edge, Chrome, Firefox, Safari
	OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
	Smart Alarm	Motion detection; person detection; vehicle detection; pet detection (beta)
	Record Modes	Motion/scheduled recording (default: motion recording)
	Protocols & Standards	HTTP, HTTPS, SSL, TCP/IP, UDP, UPNP, RTSP,RTMP, SMTP, NTP, DHCP, DNS, DDNS, P2P
	Maximal User Access	Supports up to 12 simultaneous video streams (10 substreams & 2 mainstreams); 20 users (1 admin account & 19 user accounts)
<b>Working Environment</b>	Work with	Google Assistant
	Temperature	Operating temperature: -10 °C~+55 °C (14 °F~131 °F)
	Humidity	Operating humidity: 10% ~ 90%
<b>Size &amp; Weight</b>	Waterproof	Support
	Dimension	228*147*129mm
	Weight	1.211kg
<b>Warranty</b>	Limited Warranty	2-year limited warranty. For support, visit <a href="https://support.reolink.com/hc/en-us/">https://support.reolink.com/hc/en-us/</a> .