

Indoor IR & Dual-tech detectors Pet immune Grade 3 with antimasking



jijet	Detection range	TE Opening	CHNOLOGY Pet immmunity	EN50131	Antimasking
JET PA	passive	15 meters - 90°	Yes 0/12/24 kg	Grade 2	-
JET DT	passive + microwave	15 meters - 90°	Yes 0/12/24 kg	Grade 2	-
JET DTM	passive + microwave	15 meters - 90°	Yes 0/12/24 kg	Grade 3	Yes

QUAD

Range

AVS ELECTRONICS - Italian designer and electronic alarm producer since 1974 - presents JET, its new range of 3 passive infrared detectors with Fresnel lens: JET PA (passive version) JET DT (dualtech version with passive IR and planar microwave), JET DTM (dualtech version with passive IR, planar microwave and anti-masking).

DESIGN, SAFETY AND TECHNOLOGY All JET are digital sensors with **temperature compensation**, placed in a flat housing with modern design and a spherical Fresnel lens, that presents a higher quality of detection and a better immunity to animals. A «look down» zone eliminates the blind spot below the detector for a total protection of the environment. Three LED lights (blue, yellow and green) indicate the state of the detector.

The ***Quad* type build-in electric infrared sensor** divides the functional area in 4 sectors - ie 2 times more than a conventional detector - to better distinguish environmental changes and provide a greater immunity to animals.

PET IMMUNE AND VERSATILITY Immunity to animals is an option it is possible to exclude or to select for 12 or 24 kg. To install them quickly and safely, normally closed information outputs can change their resistance values by dip-switch according to the needs of the control panel.


Two optional wall and ceiling brackets allow to install JET in the most complex positions.

EN50131 GRADE 3 AND SECURITY All JET are EN 50131 Grade 2, except JET DTM which is GRADE 3 thanks to its anti-masking solution with optical prism.

JET DT and JET DTM can be programmed in «AND» mode (infrared + microwave detection) or «AND» + «OR + « (advanced infrared or microwave detection). According to the settings and in case of failure of the "AND" mode, JET DTM can be forced in «OR +» mode for an even greater security.

MARKETS All indoor environments, with or without animals, from any regu-

lar domestic or commercial protection up to the highest banking security.











CE

AVS ELECTRONICS S.p.A.

Via Valsugana, 63, 35010, Curtarolo, (Padova), Italy Tel. +39 049 9698 411 - Fax +39 049 9698 407 avs@avselectronics.it - www.avselectronics.com



